

# POKER-MULTI-VOLTAGE BATTERY CHARGER SYSTEM

Advanced multi-cell Ferro charger excels in battery shop, rental and loaner-type installations.



- AC Input 120V AC  $\pm 5\%$ , UL-listed 20A input fuse
- Output: suitable for 12V/24/36/48V lead acid batteries
- 12V/60A, 24V/45A, 36V/30A, 48V/25A
- Input Current: 15A AC max. Equipped with NEMA 5-15A cables
- Manual timer adjustable from 0 to 24 hours max
- Manual Electromechanical switch for output voltages selection
- Cabinet with wheels and handlebar for easy handling & support for cable winding
- 24V AC auxiliary circuit with overload cut-out and 1.6A fuse

Model	AC Input	Battery Capacity
12V/60A	10.03 AMP	12V 480Ah
24V/45A	13.9 AMP	24V 360Ah
36V/30A	13.5 AMP	36V 240Ah
48V/25A	13.9 AMP	48V 200Ah
Case Size	15.7" L x 33.5" W x 12.6" D	Weight - 88 lbs.



Charlotte, NC  
877.914.8999

[info@GECIproducts.net](mailto:info@GECIproducts.net)

[www.GECIproducts.net](http://www.GECIproducts.net)